

Features

- Supports all major POS printers
- Wide selection of interfaces: printer-driven, serial, USB and OPOS
- Adjustable bill and coin compartments
- Media slot for checks and large bills
- User programmable cash drawer opening codes
- Port-powered drawers available with USB interface, no power adapter required
- Three position lock for maximum cash security
- Small form factor without sacrificing till size



CR3000

Cash Drawer

The CR3000 series of standard duty cash drawers is compact in size, enabling retailers to utilize scarce counter or shelf space for more important functions. The units make very efficient use of internal space, with the till being almost the same size as those found in larger drawers. The CR3000 series also comes with important security features: all metal construction, no exposed screws and three position locks. Bematech cash drawers work with all major brands of Point-of-Sale printers and offer a wide selection of interfaces. The CR3000 series interfaces include: printer driven, USB, serial and OPOS. The CR3003 USB cash drawers are port-powered and CR3006 serial drawers come with external power adapters.

CR3000 SPECIFICATIONS

MECHANICAL

| | |
|------------------------|---|
| Weight | 14.3lbs (6.Kg) |
| Dimensions (W x H x D) | 15.7in x 3.3in x 16.1in (39.8cm x 8.3cm x 40.9cm) |
| Bill and coin tray | Adjustable slots (default 5 bills, 5 coins) |

INTERFACE

| | |
|--------|---|
| CR3000 | Printer drive. Connected to POS printer drive circuit via cable |
| CR3003 | USB 2.0 bus powered, virtual serial port device driver |
| CR3006 | Serial interface, external power supply |

OPEN DRAWER COMMAND

| | |
|--------|--|
| CR3000 | POS printer command |
| CR3003 | User programmable security code (1 to 5 bytes) |
| CR3006 | User programmable security code (1 to 5 bytes) |

ELECTRICAL

CR3000 (Control signal from POS printer)

| | |
|------------------|-------------------|
| Pulse amplitude | 12 to 24 volts DC |
| Pulse width | 100ms to 200 ms |
| Pulse duty cycle | 10% max |

CR3003

| | |
|-------------------|------------------|
| Power supply | USB 5V bus power |
| Power consumption | 100mA max |

CR3006

| | |
|----------------------|---------------|
| Power adapter input | 120VAC-220VAC |
| Power adapter output | 5VDC, 0.8A |

NOTE

| | |
|--------|--|
| CR3000 | CR3000 supports most POS printers. Interface cable ordered separately. Please specify POS printer type when ordering cables. |
| CR3003 | No power adapter required. Keys and USB interface cable supplied. |
| CR3006 | Power adapter, keys and serial interface cable (to computer) supplied. |



www.L-TronDirect.com

800-830-9523

info@L-Tron.com

596 Fishers Station Dr | Victor, NY | 14564 | Suite 1 A

www.L-Tron.com

