

Features

- Supports all major POS printers
- Wide selection of interfaces: printer-driven, serial, USB and OPOS
- Adjustable bill and coin compartments
- Media slot for checks and large bills
- User programmable cash drawer opening codes
- Port-powered drawers available with USB interface, no power adapter required
- Three position lock for maximum cash security
- Small form factor without sacrificing till size



CR3000

Cash Drawer

The CR3000 series of standard duty cash drawers is compact in size, enabling retailers to utilize scarce counter or shelf space for more important functions. The units make very efficient use of internal space, with the till being almost the same size as those found in larger drawers. The CR3000 series also comes with important security features: all metal construction, no exposed screws and three position locks. Bematech cash drawers work with all major brands of Point-of-Sale printers and offer a wide selection of interfaces. The CR3000 series interfaces include: printer driven, USB, serial and OPOS. The CR3003 USB cash drawers are port-powered and CR3006 serial drawers come with external power adapters.

CR3000 SPECIFICATIONS

MECHANICAL

Weight	14.3lbs (6.Kg)
Dimensions (W x H x D)	15.7in x 3.3in x 16.1in (39.8cm x 8.3cm x 40.9cm)
Bill and coin tray	Adjustable slots (default 5 bills, 5 coins)

INTERFACE

CR3000	Printer drive. Connected to POS printer drive circuit via cable
CR3003	USB 2.0 bus powered, virtual serial port device driver
CR3006	Serial interface, external power supply

OPEN DRAWER COMMAND

CR3000	POS printer command
CR3003	User programmable security code (1 to 5 bytes)
CR3006	User programmable security code (1 to 5 bytes)

ELECTRICAL

CR3000 (Control signal from POS printer)	
Pulse amplitude	12 to 24 volts DC
Pulse width	100ms to 200 ms
Pulse duty cycle	10% max
CR3003	
Power supply	USB 5V bus power
Power consumption	100mA max
CR3006	
Power adapter input	120VAC-220VAC
Power adapter output	5VDC, 0.8A

NOTE

CR3000	CR3000 supports most POS printers. Interface cable ordered separately. Please specify POS printer type when ordering cables.
CR3003	No power adapter required. Keys and USB interface cable supplied.
CR3006	Power adapter, keys and serial interface cable (to computer) supplied.



www.L-TronDirect.com

800-830-9523

info@L-Tron.com

596 Fishers Station Dr | Victor, NY | 14564 | Suite 1 A

www.L-Tron.com

Get in touch with us
on social media!

